

# WS4-4D

## 100% WEBSERVER ACCESS CONTROLLER

### 4 DOORS

WS4-4D allows you to check and manage online the status of your doors and access installation anytime you want and wherever you are.

The whole system can be easily managed from any Internet browser.

To start using the WS4-4D online, just go to our website, click on the "My WS4" button and log in with your details.

To have a complete solution, we recommend you to order the electronic (WS4-4D-E) and the housing to protect it (WS4-PS5), which includes a 5A power supply.



## Practical and complete hardware

The management electronics of this 4-door unit is based on a powerful microprocessor associated with a Linux kernel. The WS4-4D electronic can be easily installed on a resistant housing, the WS4-PS5.

## WS4-4D SPECIFICATIONS

- Number of users: 2,500 users
- Door relays: 4 (2A/48 VAC/DC)
- 3 possible combinations:
  - a) 4 doors with 1 reader and 1 push button
  - b) 2 doors with 2 readers, for entry and exit
  - c) 1 door with 2 readers, for entry and exit, + 2 doors with 1 reader and 1 push button
- Access groups: 250 (categories)
- Weekly schedules: 50
- Stored events: 50,000
- Operators: 10
- If door contact is present, option for:
  - Break-in alarm
  - Door open too long alarm
  - Max. open time: 15 - 999 s
  - Pre-alarm time (reader buzzer): 0 - 99 s
- Free access period: with "Only if someone is inside" option
- Connectivity: TCP/IP 10/100/1000 Base-T mode DHCP (default) or fixed.
- HTTPS connection with XPR certificate.
- Real-time and maintenance status:
  - View of the general status of the system
  - View of door status
- Import and Export: Import and export users as .csv file (separated by TAB)
- Easy saving of data: On a USB key, in the WS4 or on the user interface
- Input - output:
  - 2 inputs: emergency, vehicle detection
  - 2 outputs: alarm, storing alarm status, presence
- Additional configuration:
  - Anti-Passback and Anti-Passback Time (0-99 min)
  - Mantrap function on all doors
- Voltage: 5A (120 - 240 V AC at 50/60 Hz, 100 VA-1.52 A with 1A fuse)
- Wiegand readers connection: via the WS4-CNV, Wiegand to RS485 converter

### Mechanical characteristics

- Electronic dimensions: 116 x 195 x 33 mm
- Brushed aluminium housing: 356 x 90 x 325 mm
- Operating temperature: 0°C to +50 °C
- Operating humidity: 0% to 85% (without condensation)
- Built-in tamper



**WS4-4D-E**  
WS4-4D electronic



**WS4-PS5**  
Universal aluminium housing,  
wall mounted, with 1 x 5A PSU