# Power supplies HPSDC series Multi-output power supply units



CODE: HPSDC v.1.0/I

NAME: Multi-output power supply units



### Features:

- supply voltage ~200 240 V
- available versions with 4, 8 or 16 outputs protected with fuses
- high efficiency (up to 86%)
- adjustable output voltage 12 15V DC
- LED optical indication
- FPS technical output of fuse activation indication
- protections:
  - SCP short circuit protection
  - OVP overvoltage protection
  - surge protection
  - · OLP overload protection
  - antisabotage protection: unwanted enclosure opening
- warranty 2 years from production date

## **DESCRIPTION**

HPSDC series stabilized power supplies are designed to supply power to HD cameras or other devices requiring stabilized voltage of 12 V DC. Output voltage is adjusted with a potentiometer within the range of 12 - 15 V DC. The PSU features 4, 8 or 16 outputs (depending on the model), protected independently by glass fuses.

A failure (an overload, a short circuit) in the output circuit will result in blowing of the fuse Fn and disconnection of the corresponding AUXn output from the power supply. The power supplies are equipped with short-circuit, overload, overvoltage and overcurrent protection. They are mounted inside a metal enclosure equipped with a signalling panel and a microswitch indicating the opening of the door (lid).

### PARAMETERS OF POWER SUPPLIES:

Model	Number of outputs	Output voltage AUX	Output current max.
HPSDC-12V4x1A	4	12 V (12 – 15 V)	4 A
HPSDC-12V8x1A	8		7 A
HPSDC-12V16x1A	16	( 101)	15 A

# Power supplies HPSDC series Multi-output power supply units



TECHNICAL DATA	HPSDC-12V4x1A	HPSDC-12V8x1A	HPSDC-12V16x1A	
Supply voltage:	~ 200 – 240 V			
Current consumption:	0,5 A	0,8 A	1,6 A	
Ripple voltage:	50mV p-p max.	50mV p-p max.	100mV p-p max.	
Power frequency:	50/60 Hz			
Inrush current:	40 A	50 A	60 A	
PSU power:	48 W max.	84 W max.	180 W max.	
Output current:	4x1 A <b>(Σ I = 4A max.)</b>	8x1 A <b>(Σ I = 7A max.)</b>	16x1 A (Σ I = <b>15A max.</b> )	
Efficiency:	86%	86%	85%	
Output voltage (factory setting):	12 V DC			
Adjustment range U <sub>AUX</sub> :	12 – 15 V DC			
Short circuit protection SCP:	4x F 1A glass fuse fast blow	8x F 1A glass fuse fast blow	16x F 1A glass fuse fast blow	
Type of glass fuse:	F1AF2A			
Overload protection OLP:	105 – 150% PSU power, automatically recovered		recovered	
Surge protection:	varistors			
Over voltage protection OVP:	>19V (activation requires disconnecting the load or supply for about approx. 1 min.)		>19V (automatic recovery)	
Protection in 230V circuit:	Glass fus	e T3,15A	Glass fuse T5A	
LED operation indication:	- LEDs on PCB of power supply unit - LED indicators on power supply's cover			
Technical output FPS – fuse failure:	relay: 1 A@ 30 V DC /50 V AC			
Operating conditions:	Temperature: -10°C ÷ +40°C relative humidity 20%90%, without condensation			
Protection class EN 62368-1:	I (first)			
Protection grade EN 60529:	IP20			
Storage temperature:	-20°C+60°C			
Vibrations and impulse waves during:	According to PN-83/T-42106			
Enclosure:	Steel sheet, 0.7mm, color RAL 9003			
Closing:	Cheese head screw (at the front), (lock assembly possible)			
Declarations, warranty:	CE, UKCA, 2 years from production date			
Notes:	Convectional cooling		Forced cooling (fan)	